



BEAMZ
MADE
EAZY

153.701 V1

CUB4 II LED

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
AUTO	Au-1		Auto program 1
	Au-2		Auto program 2
	Au-3		Auto program 3
SOUND	So-1		Sound program 1
	So-2		Sound program 2
	So-3		Sound program 3
SPEED	SP 1 - SP9		Speed value for program adjustable
SENSITIVITY	Se1 - Se9		MIC value adjustable
SILENT SCENE	OFF		The fixture is open light on music by sound program
	ON		The fixture is closed light on music by sound program
INFR	ON		Enable IR remote controller signal receiving
	OFF		Disable IR remote controller signal receiving
ADDR	4CH		4 Channels DMX mode
	10CH		10 Channels DMX mode
SLAVE	Slav		Slave
RGBW	Red	000-255	Manual settings
	Green	000-255	
	Blue	000-255	
	White	000-255	
	LED5 (5mm LED)	000-255	
	Noto (motor)	000-255	
COLOUR	C1		Red
	C2		Green
	C3		Blue
	C4		White
	C5		Red + Green
	C6		Red + Blue
	C7		Red + White
	C8		Green + Blue
	C9		Green + White
	C10		Blue + White
	C11		Green + Blue+ White
	C12		Red + Blue + White
	C13		Red + Green + White
	C14		Red + Green + Blue
	C15		Red + Green + Blue + White

DMX CHANNELS

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour Side Lenses	000-009	No function
		010-029	Red
		030-049	Green
		050-069	Blue
		070-089	White
		090-109	Red + Green
		110-129	Red + Blue
		130-149	Red + White
		150-169	Green + Blue
		170-189	Green + White
		190-209	Blue + White
		210-219	Green+ Blue+ White
		220-229	Red + Blue+ White
		230-239	Red + Green+ White
240-249	Red + Green+ Blue		
250-255	Red + Green+ Blue+ White		
2	Colour Middle Lens	000-012	No function
		013-255	Rainbow effect (every 2 values, another step)
3	Strobe	000-009	No function
		010-255	Strobe (From slow to fast)
4	Rotation	000-180	Clockwise rotation (steps)
		181-255	Counter clockwise rotation (From slow to fast)

10 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimming	000-255	Dimmer
2	Colour	000-255	Red
3	Side Lens	000-255	Green
4		000-255	Blue
5		000-255	White
6		Colour Middle Lens	000-012
		013-255	Rainbow effect (every 2 values, another step)
7	Strobe	000-009	No function
		010-255	Strobe (From slow to fast)
8	Rotation	000-180	Clockwise rotation (steps)
		181-255	Counter clockwise rotation (From slow to fast)
9	Program	000-009	No function
		010-199	Auto program
		200-255	Sound program
10	Speed	000-255	Speed for auto/sound program (From slow to fast)



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

